

Control and Power Electronics

BT356 Card Rack

Control and Power Electronics

BT356 Card Rack

Documentation

- Instructions

The BT356 card rack includes the control and power electronics for up to six tightening channels. The BT356 card rack is designed for installation in a control cabinet. Alternatively, the BT356 can be fastened to the rear mounting plate using mounting brackets. Up to 16 BT/SB or 40 tightening channels can be connected using the NK350 or NK350S network couplers and NKL network coupler cables.

Technical data

Height H [mm]	Width W [mm]	Depth D [mm]	Weight [kg]	Code	Order no.
483	310	381	7 kg	BT356	0608830253

Configuration of a BT356 card rack	Up to 5 channels, 1x BT356	Up to 40 channels, multiple BT356	
	BT356 Card Rack	First BT356 card rack	Other BT356 card racks
	Number of slots	Number of slots	Slots per BT356
VM350 power supply module	1	1	1
KE350 communication unit	1	1	
SE352/SE352M control unit	3	3	3
LT3... / LTU350/1 servo amplifier	5	5	6
Tightening channels	5	5	6
NK350S / NK350 network coupler		1 x NK350S	1 x NK350S

Accessories

Network coupler



Code	NK350	NK350S

Dummy panels



- Empty slots are closed off with dummy panels. Two versions are available: BP351 closes a KE or LT slot, BP352 simultaneously closes an SE and an LT slot.

Code	BP351	BP352
Order no.		

Mounting brackets for fastening to mounting plate



Code	Befestigungswinkel
Order no.	3608878116

Control and Power Electronics

BT356 Card Rack

Metal flange to cable the spindle to bulkhead walls

Code	Metallflansch
Order no.	1070920201

Bosch Rexroth AG

Electric Drives and Controls

P.O. Box 13 57

97803 Lohr, Germany

Bgm.-Dr.-Nebel-Str. 2

97816 Lohr, Germany

Phone +49 9352-40-0

Fax +49 9352-40-4885

www.boschrexroth.com/electrics

The data specified above only serve to describe the product.

As our products are constantly being further developed, no statements concerning a certain condition or suitability for a certain application can be derived from our information. The information given does not release the user from the obligation of own judgment and verification. It must be remembered that our products are subject to a natural process of wear and aging.